

Size  
**36"**  
A0 (91.4cm)

# CONTEX SD 36 MFP2GO

*For instant project collaboration*



**akiraDATA**<sup>®</sup>  
Deliver Technology to Your Business



Architecture  
Engineering  
and Construction



Infrastructure  
Utilities and  
Telecommunications



Education



Manufacturing  
Automotive  
and Transportation



Public sector  
and Corporate

## Complete with intuitive MFP2GO controller screen

Contex MFP2GO is our easy plug-and-play solution for your large-format printer, when you need to scan, share and copy changes to plans and drawings. The solution connects easily to your printer, giving you a nice and small footprint, and fits your existing tools and business processes. You can copy and scan to email, FTP, network, or USB – directly from the simple touch-screen controller. You get outstanding image quality, with real-time view of enhancements and preset functionality for your daily scanning needs. The Contex MFP2GO bundle includes a scanner, MFP2GO controller, and a high stand. No additional PC or software needed.

# SCANNER SPECIFICATIONS

SD 36 MFP2GO	
High-stand version <sup>1</sup>	
Settings	Right or left side controller mounting. Supported printer height from 995 to 1195 mm in 25 mm increments (39.2 to 47 inches in about 1 inch increments)
Designed to fit (USB or network) HP DesignJet T-series, Z-series, and 500/800 series, Canon iPF 600/700/900 series and EPSON SC-T series See full list of supported printers at <a href="http://context.com/mfp2go">context.com/mfp2go</a>	
Low-stand version (Side-by-side)	
Settings	Right or left side controller mounting. Working Height 821 / 846 / 871 mm (32.3 / 33.3 / 34.3 inches)
Additional printers, side-by-side EPSON STYLUS PRO, Océ, Mutoh and some HP printers. See full list at <a href="http://www.context.com/mfp2go">www.context.com/mfp2go</a>	
Scan Destinations	Copy / USB / Network / Email / FTP
File formats	TIF, JPG, PDF, PDF/A, and CALS
Scanner Specifications (See remaining specifications for the scanner under the product series)	
200 dpi RGB Color speed	1.5 inch/sec
Upgradable <sup>2</sup>	Yes
200 dpi Grayscale / Monochrome	10 inch/sec
Maximum Scan Width	36 inch (914 mm)
Maximum Media Width	38 inch (965 mm)
Optical Resolution	600 dpi
Maximum Resolution	600 dpi
Technology	Context Unibody CIS design
Context SIGMA <sup>3</sup>	•
Context CFR <sup>4</sup>	•
Maximum Media Thickness	0.08 inch (2 mm)
Accuracy	0.1% +/- 1 pixel
Data Capture (color/mono)	48-bit / 16-bit
Color Space	sRGB
Energy Star Certified	•
Power Requirements	100 – 240V, 60/50Hz, 25W
Weight	21.1 kg (46.5 lbs)
Dimensions (LxWxH)	45.6 x 12.9 x 5.5 inches (115.9 x 32.7 x 14 cm)
Certifications/compliance	CE, cUL, Gost-R, Ukr, KC, BSMI, FCC Class A, RoHS, VCCI, ENERGY STAR Certified
MFP2GO Controller specifications	
Processor	Intel Cedarview D2550 Dual Core 1.86G, L2 1M, 10W
Memory / Storage	1 GB DDR3 RMA / 160 GB SATA
OS	Windows 7 Embeded
Scanning Software	Build-inn scanning and copying software included
Language versions	Chinese, Dutch, English, French, German, Italian, Japanese, Korean, Polish, Russia, Spanish and Portuguese
Touch Screen	10.1" LED LCD, 1024x600 Pixels
Connectivity	USB or Network Printer Support / USB Scanner Support / USB Disk Support / GB Ethernet
Power Supply	65W / 19V
Weight & Dimensions	1.5 kg, WxDxH: 10.4 x 1.5 x 6.7 inches (263 x 38 x 170 mm)
Certifications/compliance	CE, cUL, CCC, KC, PSE, VCCI, FCC Class A, RoHS and ENERGY STAR Certified

- Not all supported printers will fit under the high stand, but can be used side-by-side.
- Upgrading the scanner speed will not be supported by the MFP2GO Controller. For faster scanning speeds the scanner must be connected to a full PC with optional NextImage Software.
- Signal Intensity Matching (SIGMA) is a Context Patent. Sensor heating during a scan can cause inhomogeneous images. Thanks to Context innovative thinking, our IQ Quattro and SD scanners will minimize sensor differences LIVE during a scan.

- Color Fringe Removal (CFR) is a Context Patent. Color Fringing is a natural consequence of CIS technology sequentially flashing R-G-B. Thanks to Context innovative thinking CFR will remove this problem with advanced filter technology.
- All trademarks remain the property of their respective holders, and are used only to directly describe the product being provided. Their use in no way indicates any relationship between Context A/S and the holders of the said trademarks.



Easily scan, share and copy directly from plug-and-play controller solution



Preview, crop and adjust image settings directly from controller



Scan-to-copy, -email, -network, -FTP and USB. Import images directly to standard tablets



A good ergonomic environment for left- as well as right-handed operation

Partnership :



[www.akiradata.co.id](http://www.akiradata.co.id)



Call Center  
021-830 3894



marketing  
@akiradata.co.id

## HEAD OFFICE & SHOWROOM

Jl. Dr. Saharjo No. 105C  
Tebet – Jaksel 12860  
Telp. (021) 830 3894 Fax. (021) 829 5777  
E-mail : [marketing@akiradata.co.id](mailto:marketing@akiradata.co.id)

## SERVICE CENTER

Jl. Persada Raya No. 43  
Tebet Jakarta Selatan  
Telp. (021) 829 9059